# DATA SHEET

## LED FILAMENT BULB E27 4W

G125 | DIMMABLE | 2200K | AMBER



**APPLICATION**

- Decorative and atmospheric lighting
- Indoor lighting
- Fixtures with a visible bulb
- Chandeliers and wall lights
- Pendant and table lamps
- Hospitality and retail interiors

**AVAILABLE MODELS**

| Variant | REF No |
|---|---|
| 2200K Amber | 100180 |

| | | | |
|---|---|---|---|
| E27 Socket | 4W | 300 lm | 2 YEARS |
| 2200K Colour temp. | DIMMABLE Dimming | G125 Bulb shape | AMBER Glass colour |

# DATA SHEET

VARNALUX

## LED FILAMENT BULB E27 4W

G125 | DIMMABLE | 2200K | AMBER

| GENERAL | |
|---|---|
| **Article number** | 100180 |
| **Product type** | LED filament bulb |
| **Bulb shape** | G125 |
| **Socket / base** | E27 |

| ELECTRICAL DATA | |
|---|---|
| **Power (consumption)** | 4W |
| **Driver** | IC driver |
| **Dimmable** | Yes |
| **Energy efficiency class** | A |

| PHOTOMETRICAL DATA | |
|---|---|
| **Luminous flux** | 300 lm |
| **Luminous efficiency** | 75 lm/W |
| **Colour temperature (Kelvin)** | 2200K |
| **Colour** | Amber |
| **Colour rendering index (CRI)** | > 80 |
| **Beam angle** | 360° |

| LIFESPAN & WARRANTY | |
|---|---|
| **Lifespan** | 15.000 hrs |
| **Warranty** | 2 years |

| DIMENSIONS & PACKAGING | |
|---|---|
| **Height** | 136 mm |
| **Diameter** | 95 mm |

| ADDITIONAL INFORMATION | |
|---|---|
| **Material** | Glass |
| **IP rating** | IP22 |

# DATA SHEET

VARNALUX

## LED FILAMENT BULB E27 4W

G125 | DIMMABLE | 2200K | AMBER

### INSTALLATION

**STEP 1** **Check the specification**

Read the specification first and make sure the service environment matches the specified conditions (IP22, indoor use).

**STEP 2** **Confirm the supply**

Confirm the applicable power supply before using the bulb.

**STEP 3** **Switch off the power**

Power must be cut off before installation. Make sure the switch is off before connecting to the power supply, to prevent electric shock.

**STEP 4** **Fit the bulb**

Screw the bulb into a matching E27 socket.

**STEP 5** **Dimming**

Dimmable version: use the bulb only on a compatible dimmer circuit.

**STEP 6** **Switch on**

Switch on the power supply and check the light output.

**SAFETY NOTICE:**

- Read the specification first and make sure the service environment matches the conditions in the specification before using.
- Confirm the applicable power supply before using.
- Make sure the switch is off before connecting to the power supply, to prevent electric shock.
- Operation against the rules may damage your property and even harm your personal safety.
- Dangerous high voltage: non-professionals are not allowed to maintain the product.
- IP22: for indoor use only. Keep the bulb away from moisture.