# DATA SHEET

VARNALUX

## LED FILAMENT CANDLE E14 5W

B35 SHARP SHAPE | DIMMABLE | 2700K | CLEAR



**APPLICATION**

- Decorative and atmospheric lighting
- Indoor lighting
- Fixtures with a visible bulb
- Chandeliers and wall lights
- Pendant and table lamps
- Hospitality and retail interiors

**AVAILABLE MODELS**

| Variant | REF No |
|---|---|
| 2700K Clear | 100202 |

| | | | |
|---|---|---|---|
| E14 Socket | 5W | 400 lm | 2 2 YEARS |
| 2700K Colour temp. | DIMMABLE Dimming | B35 SHARP SHAPE Bulb shape | CLEAR Glass colour |

# DATA SHEET

VARNALUX

## LED FILAMENT CANDLE E14 5W

B35 SHARP SHAPE | DIMMABLE | 2700K | CLEAR

| GENERAL | |
|---|---|
| **Article number** | 100202 |
| **Product type** | LED filament candle |
| **Bulb shape** | B35 Sharp Shape / Candle |
| **Socket / base** | E14 |

| ELECTRICAL DATA | |
|---|---|
| **Power (consumption)** | 5W |
| **Driver** | IC Driver |
| **Dimmable** | Yes |
| **Power factor** | > 0.40 |
| **Energy efficiency class** | G |

| PHOTOMETRICAL DATA | |
|---|---|
| **Luminous flux** | 400 lm |
| **Luminous efficiency** | 80 lm/W |
| **Colour temperature (Kelvin)** | 2700K |
| **Light colour** | Warm White |
| **Glass colour** | Clear |
| **Colour rendering index (CRI)** | > 80 |
| **Beam angle** | 360° |

| LIFESPAN & WARRANTY | |
|---|---|
| **Lifespan** | 15.000 hrs |
| **Warranty** | 2 years |

| ADDITIONAL INFORMATION | |
|---|---|
| **Material** | Glass |
| **IP rating** | IP20 |
| **Operating temperature** | -20 °C to 40 °C |

# DATA SHEET

VARNALUX

## LED FILAMENT CANDLE E14 5W

B35 SHARP SHAPE | DIMMABLE | 2700K | CLEAR

### INSTALLATION

**STEP 1** **Check the specification**

Read the specification first and make sure the service environment matches the specified conditions (IP20, indoor use).

**STEP 2** **Confirm the supply**

Confirm the applicable power supply before using the bulb.

**STEP 3** **Switch off the power**

Power must be cut off before installation. Make sure the switch is off before connecting to the power supply, to prevent electric shock.

**STEP 4** **Fit the bulb**

Screw the bulb into a matching E14 socket.

**STEP 5** **Dimming**

Dimmable version: use the bulb only on a compatible dimmer circuit.

**STEP 6** **Switch on**

Switch on the power supply and check the light output.

**SAFETY NOTICE:**

- Read the specification first and make sure the service environment matches the conditions in the specification before using.
- Confirm the applicable power supply before using.
- Make sure the switch is off before connecting to the power supply, to prevent electric shock.
- Operation against the rules may damage your property and even harm your personal safety.
- Dangerous high voltage: non-professionals are not allowed to maintain the product.
- IP20: for indoor use only. Keep the bulb away from moisture.