DATA SHEET

VARNALUX

LED FILAMENT BULB E14 5W

B35 BENT SHAPE | DIMMABLE | 2700K | CLEAR



APPLICATION

- Decorative and atmospheric lighting
- Indoor lighting
- Fixtures with a visible bulb
- Chandeliers and wall lights
- Pendant and table lamps
- Hospitality and retail interiors

AVAILABLE MODELS

Variant	REF No
2700K Clear	100204

E14 Socket	5W	400 lm	2 2 YEARS
2700K Colour temp.	DIMMABLE Dimming	B35 BENT SHAPE Bulb shape	CLEAR Glass colour

DATA SHEET

VARNALUX

LED FILAMENT BULB E14 5W

B35 BENT SHAPE | DIMMABLE | 2700K | CLEAR

GENERAL	
Article number	100204
Product type	LED filament bulb
Bulb shape	B35 Bent Shape / Candle
Socket / base	E14

ELECTRICAL DATA	
Power (consumption)	5W
Driver	IC Driver
Dimmable	Yes
Power factor	> 0.5

PHOTOMETRICAL DATA	
Luminous flux	400 lm
Luminous efficiency	80 lm/W
Colour temperature (Kelvin)	2700K
Light colour	Warm White
Glass colour	Clear
Colour rendering index (CRI)	> 80
Beam angle	360°

LIFESPAN & WARRANTY	
Lifespan	20.000 hrs
Warranty	2 years

ADDITIONAL INFORMATION	
Material	Glass
IP rating	IP22

DATA SHEET

VARNALUX

LED FILAMENT BULB E14 5W

B35 BENT SHAPE | DIMMABLE | 2700K | CLEAR

INSTALLATION

STEP 1 **Check the specification**

Read the specification first and make sure the service environment matches the specified conditions (IP22, indoor use).

STEP 2 **Confirm the supply**

Confirm the applicable power supply before using the bulb.

STEP 3 **Switch off the power**

Power must be cut off before installation. Make sure the switch is off before connecting to the power supply, to prevent electric shock.

STEP 4 **Fit the bulb**

Screw the bulb into a matching E14 socket.

STEP 5 **Dimming**

Dimmable version: use the bulb only on a compatible dimmer circuit.

STEP 6 **Switch on**

Switch on the power supply and check the light output.

SAFETY NOTICE:

- Read the specification first and make sure the service environment matches the conditions in the specification before using.
- Confirm the applicable power supply before using.
- Make sure the switch is off before connecting to the power supply, to prevent electric shock.
- Operation against the rules may damage your property and even harm your personal safety.
- Dangerous high voltage: non-professionals are not allowed to maintain the product.
- IP22: for indoor use only. Keep the bulb away from moisture.