DATA SHEET

VARNALUX

LED T5 TUBE 145CM 25W

ALUMINIUM T5 | 140 LM/W | G5




APPLICATION

- Commercial spaces
- Offices
- Institutional buildings
- General lighting

AVAILABLE MODELS


Color Temp	REF No
3000K	100478
4000K	100479
6000K	100480



KEY FEATURES

- 3500 lm at 140 lm/W from 25W
- Aluminium + PC, optical PC diffuser (milk option)
- Sanan LEDs, 120° beam angle, flicker-free
- Single-ended input, G5 base
- 50,000 hours lifetime
- 5 years warranty

COLOUR TEMPERATURE



Warm white
REF 100478

Neutral white
REF 100479

Cool white
REF 100480

DATA SHEET

VARNALUX

LED T5 TUBE 145CM 25W

ALUMINIUM T5 | 140 LM/W | G5

ELECTRICAL DATA	
Wattage (Consumption)	25W
Voltage	AC200-240V
Max. current	0.11A
Operating voltage	DC40-86V
Constant current	280mA
Power Factor	>=0.9
Input type	Single-ended input

PHOTOMETRICAL DATA	
Temperature (Kelvin)	3000K / 4000K / 6000K
Light color	Warm, neutral or cool white
Lumen (all CCT)	3500 lm
Luminous efficiency	140 lm/W
Beam angle	120°
Color Rendering Index (CRI)	>80
LED type	SMD2835
LED brand	Sanan

CAPABILITIES	
Dimmable	No
Flicker-free	Yes
Structure	Non-rotatable
Base	G5


LIFESPAN & WARRANTY	
Lifespan	50,000 hours
Warranty	5 years

DIMENSIONS	
Size	1450mm
Product dim.	1448 x D22mm

ADDITIONAL INFORMATION	
Construction	Aluminum with PC
Diffuser	Optical PC (milk option)
IP Rating	IP20

AVAILABLE MODELS

Color Temp	REF No
3000K	100478
4000K	100479
6000K	100480



Schematic drawing, not to scale. Dimensions in mm.

DATA SHEET

VARNALUX

LED T5 TUBE 145CM 25W

ALUMINIUM T5 | 140 LM/W | G5

USER MANUAL | HOW TO USE

STEP 1 **Unpack and check**

Take the tube out of the packaging and check it for damage. If any damage is visible, do not install or use it.

STEP 2 **Turn off the power**

Switch off the mains supply before fitting or replacing a tube. Installation must be done by a qualified person.

STEP 3 **Fit the tube**

Insert the G5 pins into the sockets of the fixture and turn the tube until it is held securely.

STEP 4 **Check compatibility**

The tube has single-ended input for AC 200-240V. Make sure the fixture is compatible before installing the tube.

STEP 5 **Turn on the power**

Switch on the mains supply. The tube is non-dimmable: do not use it with a dimmer.

STEP 6 **Maintenance**

Replace a damaged tube immediately. Dispose of the tube according to local regulations for electrical waste.

SAFETY NOTICE:

- Installation must be done by a qualified person only; always switch off the mains supply first.
- If the tube or its pins are damaged, the product must not be used.
- The tube is non-dimmable and must not be used with dimmers.
- IP20: for indoor use in dry locations only.
- Avoid looking directly into the LEDs for extended periods. Do not shine the light in anyone's eyes.
- Keep the tube and packaging material away from children and pets.
- Do not disassemble or modify the tube.