DATA SHEET

VARNALUX

LED TRI-PROOF HOUSING 120CM

IP65 | FOR T8 LED TUBES | LINKABLE | 36W




APPLICATION

- Industrial areas
- Parking garages
- Warehouses and storage rooms
- Damp and dusty rooms
- Corridors and utility areas

AVAILABLE MODELS

Variant	REF No
Single	100517
Double	100518



KEY FEATURES

- 36W tri-proof housing, IP65 protection
- Single and Double variants
- 5400 lm at 150 lm/W
- Philips driver, flicker-free operation
- Linkable on both sides via cable glands
- 50,000 hours lifetime
- 5 years warranty

AVAILABLE VARIANTS

SINGLE
REF 100517

DOUBLE
REF 100518

DATA SHEET

VARNALUX

LED TRI-PROOF HOUSING 120CM

IP65 | FOR T8 LED TUBES | LINKABLE | 36W

PRODUCT INFORMATION	
Product type	Tri-proof housing for T8 LED tubes
Configurations	Single / Double

ELECTRICAL DATA	
Wattage (Consumption)	36W
Voltage	220-240V
Driver	Philips
Dimming	No

PHOTOMETRICAL DATA	
Luminous flux	5400 lm
Luminous efficiency	150 lm/W

CAPABILITIES	
Dimmable	No
Flicker-free	Yes
Linkable	Yes, both sides
Connection	Cable glands for series installation


LIFESPAN & WARRANTY	
Lifespan	50,000 hours
Warranty	5 years

DIMENSIONS	
Size	1285 mm

ADDITIONAL INFORMATION	
IP Rating	IP65
Driver	Philips

AVAILABLE MODELS

Variant	REF No
Single	100517
Double	100518



Schematic drawing, not to scale. Dimensions in mm.

DATA SHEET

VARNALUX

LED TRI-PROOF HOUSING 120CM

IP65 | FOR T8 LED TUBES | LINKABLE | 36W

USER MANUAL | HOW TO USE

STEP 1 **Unpack and check**

Take the fixture out of the packaging and check it for damage. If any damage is visible, do not install or use it.

STEP 2 **Turn off the power**

Switch off the mains supply before starting any work on the fixture. Installation must be done by a professional electrician only.

STEP 3 **Mount the fixture**

Fix the housing securely to a suitable flat surface with fixings suited to the fixture and the surface. Never cover the fixture with other objects.

STEP 4 **Connect the cable**

Lead the supply cable through the cable gland and connect it to 220-240V. For series installation, link the fixtures on both sides via the cable glands. Tighten the glands to keep the IP65 protection.

STEP 5 **Close and turn on**

Insert compatible T8 LED tube(s) where applicable (1 for Single, 2 for Double), close the cover and secure the clips. Switch on the mains supply.

STEP 6 **Maintenance**

Maintenance and repair by trained professionals only. In case of damage to the cable or the housing, stop using the fixture.

SAFETY NOTICE:

- Installation must be done by a professional electrician only; non-professionals must not install, disassemble or connect wires.
- If the cable or the housing is damaged, the product must not be used.
- Close the cover and tighten all cable glands correctly; the IP65 protection only applies when the fixture is closed properly.
- The fixture is non-dimmable and must not be used with dimmers.
- Never cover the fixture and keep it away from open flames and external heat sources.
- Avoid looking directly into the light source for extended periods.
- Keep packaging material away from children and pets.