DATA SHEET

VARNALUX

LED STREET LIGHT 30W PREMIUM

40MM MOUNTING | VARNALUX DRIVER | 3000K / 4000K



APPLICATION

- Streets
- Pathways
- Parking areas
- Public spaces
- Commercial spaces

AVAILABLE MODELS	
Color Temp	REF No
3000K	100131
4000K	100132

30W | 150 lm/W | 5 YEARS | 3000/4000K

40mm MOUNT HOLE





DATA SHEET

VARNALUX

LED STREET LIGHT 30W PREMIUM

40MM MOUNTING | VARNALUX DRIVER | 3000K / 4000K

ELECTRICAL DATA	
Wattage (Consumption)	30W

PHOTOMETRICAL DATA	
Temperature (Kelvin)	3000K or 4000K
Light color	Warm white or neutral white
Luminous efficiency	150 lm/W
Lumen	4,500 lm
Beam angle	140° x 70°
Color Rendering Index (CRI)	70 Ra
LED	Lumileds / Sanan

CAPABILITIES	
Dimmable	No
Mounting hole size	40 mm

LIFESPAN & WARRANTY	
Warranty	5 years

ADDITIONAL INFORMATION	
Driver	Varnalux
LED	Lumileds / Sanan
Mounting hole	40 mm

AVAILABLE MODELS

Color Temp	REF No
3000K	100131
4000K	100132

DATA SHEET

VARNALUX

LED STREET LIGHT 30W PREMIUM

40MM MOUNTING | VARNALUX DRIVER | 3000K / 4000K

USER MANUAL | HOW TO INSTALL AND USE

STEP 1 **Connect the wires**

Connect the supply wires: L = live, N = neutral, yellow-green = ground. Switch the power off before starting.

STEP 2 **Install the pole**

Put the pole into the lamp arm and fix the screw with a hexagonal wrench. Be careful not to lock the screw yet.

STEP 3 **Adjust the angle**

Adjust the lamp body horizontally so that the lamp body and the ground are parallel. Then tighten the screws with a hexagonal wrench.

STEP 4 **Assembly completed**

The luminaire is assembled and ready for use. Keep the fixture horizontal during installation and all later use.

SAFETY NOTICE:

- Installation must be done by professionals only; non-professionals must not install, disassemble or connect wires (high voltage).
- If the power line or the housing is damaged, the product must be treated as defective and must not be used.
- Use the light out of its package and check it for transport damage before installation. If any damage is shown, do not install or use it.
- Never cover the luminaire and keep it away from open flames and external heat sources.
- Avoid looking directly into the LED beam, especially for extended periods. Do not shine the light in anyone's eyes.
- Keep packaging material away from children and pets (risk of suffocation, small parts). Never leave children unattended near the luminaire.
- Maintenance by trained professionals only. Unauthorised disassembly may void the after-sales service.
- After its service life the product needs an inspection or special treatment for disposal.